Time: 3 Hours Marks: 80

- NB. 1. Question No. 1 is **compulsory**.
 - 2. Attempt any three out of remaining five questions.
 - 2. Figures to right indicate full marks.
 - 3. Assume data wherever required and state it clearly.

Q1 20

- a) Stating the relationship between PDF and CDF, give the properties of PDF.
- b) Define Entropy of an information source? When is the entropy maximum?
- c) Over a long transmission line draw the following data format for the binary sequence 10011101011.
 - i) Unipolar NRZ
- ii) Polar RZ
- iii) Manchester

Select the best and justify the answer.

- d) Explain the role of Hamming distance in error detection & correction?
- e) For impulse responses $g^1 = \{1,1,0\}$, $g^2 = \{0,1,0\}$, $g^3 = \{1,1,1\}$ design the state diagram.

Q2

a) A discrete memoryless source has an alphabet of six symbol with their probabilities as shown:

| Symbol | M_1 | M_2 | M_3 | M_4 | M_5 | M_6 |
|-------------|--------|-------|-------|-------|-------|---------|
| Probability | 0.3 | 0.25 | 0.15 | 0.12 | 0.08 | 0.10 |
| 8,4 | 2 26 0 | 4 00 | 7.8 A | 0.7.6 | 9,0,4 | 10 00 V |

- i) Determine the Minimum Variance Huffman code-words and average code-word length and hence find Entropy of the system.
- ii) Verify the average code-word length using Shannon Fano.
- iii) Compare and comment on the results of both
- b) A convolution encoder has a constraint length of 3 and code rate of 1/3. The impulses for each are $g^1=100$ $g^2=101$ $g^3=111$. Draw
 - i) encoder
 - ii) state diagram
 - iii) code transfer function

Q3

a) State and prove the Conditional Probability.

10

b) Draw the signal space diagram for 16-PSK and 16-QAM and find their error probability. Also draw their PSD and determine bandwidth.

10

10

Q4

a) A parity check matrix of a (7,4) Hamming code is given as follows:

10

$$H = \begin{bmatrix} 1 & 1 & 1 & 0 & 1 & 0 & 0 \\ 0 & 1 & 1 & 1 & 0 & 1 & 0 \\ 1 & 1 & 0 & 1 & 0 & 0 & 1 \end{bmatrix}$$

- i) Find Generator matrix, using which find out the code-words of 1100 and 0101,
- ii) Determine the error detecting and correcting capability of system,
- iii) Draw the encoder for the above block code.
- b) Sketch the encoder and syndrome calculator for the generator polynomial 10

71272

Paper / Subject Code: 32202 / Digital Communication

 $g(x)=1+x^2+x^3$ and obtain the syndrome for the received code-word 1101011.

Q5

- a) Discuss the problem of inter symbol interference (ISI). Explain the measures to 10 be taken to reduce ISI. How to study ISI using eye pattern?
- b) Consider a convolution encoder with the constraint length K=3 and $g^1 = \{1,0,1\}$ and $g^2 = \{0,1,1\}$. Find the code vector for the message stream 11010 using time domain approach. Verify the code vector using transform approach.

Q6

Explain with the required diagrams (Any Three):

20

- a) Modified duo-binary encoder
- b) Shannon Hartley Theorem for Channel Capacity
- c) Need for error control codes.
- d) Define the following terms and give their significance
 - (i) Mean (ii) Central moment (iii) Variance (iv) Standard deviation
